

Lecture Outline for Monday, Dec. 2, 2024

1. Crank-Nicholson Method (an implicit FD method) applied to heat equation

$$c \frac{\partial^2 u}{\partial x^2} = \frac{\partial u}{\partial t}$$

- a. Issues with explicit FD method:
 - i. centered difference for x -derivative and forward difference for t -derivative
 - ii. mixed differencing reduces accuracy slightly for a given Δx
 - iii. stability criterion limits size of Δt
- b. One alternative: center all derivatives at time $t + 0.5\Delta t$ instead of at t or $t + \Delta t$. FD approximations become

$$t\text{-derivative: } \frac{\partial u(x, t + 0.5\Delta t)}{\partial t} \approx \frac{u(x, t + \Delta t) - u(x, t)}{\Delta t}$$

$$x\text{-derivative: } \frac{\partial^2 u(x, t + 0.5\Delta t)}{\partial x^2} \approx \frac{u(x + \Delta x, t + 0.5\Delta t) - 2u(x, t + 0.5\Delta t) + u(x - \Delta x, t + 0.5\Delta t)}{\Delta x^2}$$

- c. Indexing doesn't allow half time-steps, so

$$\begin{aligned} \frac{\partial^2 u(x, t + 0.5\Delta t)}{\partial x^2} &\approx \frac{1}{2} \left[\frac{\partial^2 u(x, t + \Delta t)}{\partial x^2} + \frac{\partial^2 u(x, t)}{\partial x^2} \right] \\ &\approx \frac{1}{2} \left[\frac{u(x + \Delta x, t + \Delta t) - 2u(x, t + \Delta t) + u(x - \Delta x, t + \Delta t)}{\Delta x^2} \right. \\ &\quad \left. + \frac{u(x + \Delta x, t) - 2u(x, t) + u(x - \Delta x, t)}{\Delta x^2} \right] \end{aligned}$$

- d. Approximation of x -derivative using index notation:

$$\frac{\partial^2 u(x, t + 0.5\Delta t)}{\partial x^2} \approx \frac{1}{2\Delta x^2} (u_{i+1, j+1} - 2u_{i, j+1} + u_{i-1, j+1} + u_{i+1, j} - 2u_{i, j} + u_{i-1, j})$$

- e. FD approximation of heat equation becomes

$$\frac{c}{2\Delta x^2} (u_{i+1, j+1} - 2u_{i, j+1} + u_{i-1, j+1} + u_{i+1, j} - 2u_{i, j} + u_{i-1, j}) = \frac{u_{i, j+1} - u_{i, j}}{\Delta t}$$

(continued on next page)

- f. Multiply both sides by $2\Delta x^2/c$, then gather $j + 1$ (new) terms on the left and j (old) terms on the right:

$$u_{i-1,j+1} - \left(2 + \frac{2\Delta x^2}{c\Delta t}\right) u_{i,j+1} + u_{i+1,j+1} = -u_{i-1,j} + \left(2 - \frac{2\Delta x^2}{c\Delta t}\right) u_{i,j} - u_{i+1,j}$$

Left-hand side has terms at three adjacent locations ($i + 1$, i , and $i - 1$), which leads to a set of coupled equations, that is, a system of equations (matrix equation).

- g. Special cases at boundaries. For Dirichlet BCs ($u_{1,j+1} = u_a$ and $u_{N_x,j+1} = u_b$) use:

at $x = a$, substitute $u_{1,j+1} = u_{a,j+1}$ and $u_{1,j} = u_{a,j}$ (if u_a does not vary with time, then substitute $u_{1,j+1} = u_{1,j} = u_a$):

$$\begin{aligned} u_{a,j+1} - \left(2 + \frac{2\Delta x^2}{c\Delta t}\right) u_{2,j+1} + u_{3,j+1} &= -u_{a,j} + \left(2 - \frac{2\Delta x^2}{c\Delta t}\right) u_{2,j} - u_{3,j} \\ \rightarrow -\left(2 + \frac{2\Delta x^2}{c\Delta t}\right) u_{2,j+1} + u_{3,j+1} &= -u_{a,j+1} - u_{a,j} + \left(2 - \frac{2\Delta x^2}{c\Delta t}\right) u_{2,j} - u_{3,j} \end{aligned}$$

at $x = b$, substitute $u_{N_x,j+1} = u_{b,j+1}$ and $u_{N_x,j} = u_{b,j}$ (if u_b does not vary with time, then substitute $u_{N_x,j+1} = u_{N_x,j} = u_b$):

$$\begin{aligned} u_{N_x-2,j+1} - \left(2 + \frac{2\Delta x^2}{c\Delta t}\right) u_{N_x-1,j+1} + u_{b,j+1} &= -u_{N_x-2,j} + \left(2 - \frac{2\Delta x^2}{c\Delta t}\right) u_{N_x-1,j} - u_{b,j} \\ \rightarrow u_{N_x-2,j+1} - \left(2 + \frac{2\Delta x^2}{c\Delta t}\right) u_{N_x-1,j+1} &= -u_{N_x-2,j} + \left(2 - \frac{2\Delta x^2}{c\Delta t}\right) u_{N_x-1,j} - u_{b,j} - u_{b,j+1} \end{aligned}$$

- h. Note that the first equation involves terms at $i = 2$ and $i = 3$ (but not at $i = 1$) and that the last equation involves terms at $i = N_x - 2$ and $i = N_x - 1$ (but not at $i = N_x$). The total number of equations is therefore equal to $N_x - 2$, which results in an $(N_x - 2) \times (N_x - 2)$ system of equations:

$$\begin{bmatrix} -\alpha & 1 & 0 & 0 & \cdots & 0 \\ 1 & -\alpha & 1 & 0 & \cdots & 0 \\ 0 & 1 & -\alpha & 1 & & \vdots \\ \vdots & & & \ddots & & 0 \\ 0 & \cdots & 0 & 1 & -\alpha & 1 \\ 0 & \cdots & 0 & 0 & 1 & -\alpha \end{bmatrix} \begin{bmatrix} u_{2,j+1} \\ u_{3,j+1} \\ u_{4,j+1} \\ \vdots \\ u_{N_x-2,j+1} \\ u_{N_x-1,j+1} \end{bmatrix} = \begin{bmatrix} -u_{a,j+1} - u_{a,j} + \beta u_{2,j} - u_{3,j} \\ -u_{2,j} + \beta u_{3,j} - u_{4,j} \\ -u_{3,j} + \beta u_{4,j} - u_{5,j} \\ \vdots \\ -u_{N_x-3,j} + \beta u_{N_x-2,j} - u_{N_x-1,j} \\ -u_{N_x-2,j} + \beta u_{N_x-1,j} - u_{b,j} - u_{b,j+1} \end{bmatrix},$$

$$\text{where } \alpha = 2 + \frac{2\Delta x^2}{c\Delta t} \quad \text{and} \quad \beta = 2 - \frac{2\Delta x^2}{c\Delta t}$$